

PTS-60-3AR



Left rear view

Engine: Perkins 1104D-44TG1
Generator: Marathon361PSL1603
Automatic Voltage Regulator
Main Line Set Mounted Circuit Breaker
4" Steel Channel Skid-Base
Vibration Isolators
High-Ambient Radiator Cooled with Blower Fan, Fan Guards
Dry Type Air Cleaner
Spin on Lube Oil Filter, Spin on Fuel Oil Filters
Critical Exhaust Silencer
Stainless Steel Exhaust Flex
24-Volt Direct Current Starting Motor, 24-Volt Direct Current Battery Charging Alternator, 24 VDC Fuel Pump
Safety Shutdowns for High Water Temperature and Low Oil Pressure
Set Mounted Start/Stop Switch and Hour Meter
Dimensions (Open): L= 67" W= 27" H= 43"
Digital Engine/Generator Control Panel:
AC Ammeter, AC Voltmeter, Frequency Meter,
Running Time Meter, Engine Oil Pressure Gauge, Water Temperature Gauge,
Line Reading Selector Switch, Off/Auto/Manual Switch, Auto Start Engine Controller
With Fault Lights for Over Speed, Over Crank, Low Oil Pressure, and High Water Temperature.
Dual Gel Cell Battery, with Rack and Cables

Optional:

Sound Attenuated Weather Resistant Aluminum Polyester Powder Coated Enclosure Dimensions: L= 94" W=42.5" H=50"
Analog Meter Package: Amp Meter, Volt Meter, Hertz Meter, Oil Pressure Gauge, and Coolant Temperature Gauge.
Receptacle Package: cost based on requirements.



Right rear view



Open unit shown with Optional Analog Panel

